

10











ELECTRICAL SYSTEM

[1] WIRING DIAGRAM

• Key Switch

Terminal	B	AC	G1	G2	ST	OFF
Key Position						
HEAT	●	●	●			
OFF	●					●
ON	●	●				
START	●	●		●	●	

• Combination Switch

Head light switch					Hazard light switch			
Color	R	Y	RL	RY	Color	G	GY	GB
	B1	T	1	2		B22	R	L
OFF					1			
1					OFF			
2					2			

• Color of Wiring

W ----- White	RY ----- Red / Yellow
R ----- Red	BW ----- Black / White
L ----- Blue	BL ----- Black / Blue
Y ----- Yellow	BR ----- Black / Red
B ----- Black	BY ----- Black / Yellow
G ----- Green	GW ----- Green / White
Br ----- Brown	GY ----- Green / Yellow
Or ----- Orange	GB ----- Green / Black
Lg ----- Light green	GR ----- Green / Red
WG ----- White / Green	LW ----- Blue / White
WB ----- White / Black	LY ----- Blue / Yellow
WR ----- White / Red	YL ----- Yellow / Blue
WL ----- White / Blue	YB ----- Yellow / Black
RW ----- Red / White	BrW ----- Brown / White
RL ----- Red / Blue	BrR ----- Brown / Red

